

TRANSISTOR NUMBER	PM OALT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
AF282	PG	TO1H	L02	25V	25V	2V	10MA	75C	60MWF	40M	3P	40/150	1MA	VLA	OBS	AF106	2N3283	2
AF284	PG	TO1H	L02	25V	25V	2V	10MA	75C	60MWF	40M	3P	25/150	1MA	VLA	OBS	AF106	2N3283	2
AF306	PG	TO92	L74	25V	18V	OV3	15MA	90C	60MWF	100M	1R5	10MN	10MA	FVG	SID	AF106	2N3323	1
AF339	PG	TO92	L74	20V	15V	.3V	12MA	85C	120MWF	400M	1P5	40TP	2MA	VLA	SID	AF106	2N3323	2
AF367	PG	X32	L71	20V	15V	OV3	10MA	90C	60MWF	350M	OR7	10MN	2MA	ULA	VAL	AF239	2N3783	1
AF369	PG	X32	L71	20V	15V	OV3	10MA	90C	60MWF	250M	.	10MN	2MA	ULA	VAL	AF239	2N3783	1
AF379	PG	X37	L82	18V	13V	OV3	20MA	90C	100MWF	600M	1P	40MN	10MA	ULA	VAL	AF239	2N3783	1
AFY10	PG	TO5	L04	30V	15V	1V	70MA	90C	560MWC	150M	2P8	10MN	2MA	VMS	SID	AFY18	2N2382	1
AFY11	PG	TO39	L04	30V	15V	1V	70MA	90C	560MWC	150M	2P8	10MN	2MA	VLA	SID	AFY18	2N2382	1
AFY12	PG	TO72	L06	25V	18V	OV5	10MA	90C	112MWF	120M	.	25/120	1MA	VLA	SID	AF106	2N3283	1
AFY13	PG	TO72	L06	25V	18V	OV7	50MA	85C	60MWF	30M	.	40MN	1MA	FVG	OBS	AF124	2N990	1
AFY14	PG	X04	L01	40V	20V	1V	250MA	80C	150MWF	40M	5P	40MN	1MA	RLA	TFK	AF124	2N990	0
AFY15	PG	TO18	L01	22V	12V	8V	50MA	85C	100MWF	8M	.	30MN	500UA	ALN	TFK	OC44N	2N2706	1
AFY16	PG	TO72	L06	30V	25V	OV5	10MA	90C	112MWF	350M	OR4	10MN	1.5MA	ULA	VAL	AF239	2N3783	1
AFY17	PG	TO72	L06	25V	15V	.	7MA	75C	33MWF	250M	1.2P	40/150	1.5MA	VLG	OBS	AF239SS	2N3783	2
AFY18	PG	TO39	L04	30V	15V	OV7	100MA	90C	560MWF	300M	3P	40MN	10MA	VMA	SID	AFY18	.	1
AFY18C	PG	TO39	L04	30V	15V	OV7	100MA	90C	560MWF	300M	3P	40/120	10MA	VMA	SID	AFY18	.	1
AFY18D	PG	TO39	L04	30V	15V	OV7	100MA	90C	560MWF	300M	3P	100MN	10MA	VMA	SID	AFY18	.	1
AFY18E	PG	TO39	L04	30V	15V	OV7	100MA	90C	560MWF	300M	3P	200MN	10MA	VMA	SID	AFY18	.	1
AFY19	PG	TO39	L04	32V	32V	.	300MA	90C	800MWF	200M	.	20MN	80MA	VMP	MUB	AFY18	2N2382	1
AFY20	PG	TO1	L02	15V	10V	.	100MA	75C	150MWF	.	20P	30/100	5MA	RLS	OBS	ASY27	2N1307	2
AFY21	PG	TO1	L02	15V	10V	.	100MA	75C	150MWF	5M	20P	60/100	5MA	RLS	OBS	ASY27	2N1307	2
AFY22	PG	TO1	L02	15V	10V	.	100MA	75C	150MWF	5M	20P	90/150	5MA	RLS	OBS	ASY27	2N1307	2
AFY23	PG	TO1	L02	15V	10V	.	100MA	75C	150MWF	10M	20P	60/100	5MA	RLS	OBS	ASY27	2N1307	2
AFY24	PG	TO1	L02	15V	10V	.	100MA	75C	150MWF	10M	20P	90/150	5MA	RLS	OBS	ASY27	2N1307	2
AFY25	PG	TO39	L57	12V	10V	.	10MA	75C	40MWF	1G	2P	3MN	3.5MA	TUO	OBS	AF239	2N3783	2
AFY26	PG	TO39	L57	12V	10V	.	10MA	75C	40MWF	2P	2P	3MN	3.5MA	TUM	OBS	AF239	2N3783	2
AFY29	PG	TO72	L06	25V	15V	OV7	50MA	85C	90MWF	20M	.	40MN	1MA	FVG	OBS	AF106	2N3283	1
AFY30	PG	TO39	L04	10V	10V	.	100MA	75C	500MWF	400M	2P6	60/100	10MA	UMG	OBS	.	2	
AFY31	PG	TO39	L04	10V	10V	.	100MA	75C	500MWF	400M	2P6	90/150	10MA	UMG	OBS	.	2	
AFY32	PG	TO39	L04	10V	10V	.	100MA	75C	500MWF	400M	2P6	130MN	10MA	UMG	OBS	.	2	
AFY33	PG	TO39	L04	20V	15V	.	70MA	75C	560MWF	200M	2P8	30/220	10MA	VMG	OBS	.	2	
AFY34	PG	OBS	OBS	40V	.	.	20MA	90C	.	1G5	.	10MN	2MA	SLA	SID	.	1	
AFY35	PG	TO39	L04	12V	10V	.	50MA	75C	500MWF	300M	2P6	90/150	2MA	VLG	OBS	.	2	
AFY36	PG	TO39	L04	12V	10V	.	50MA	75C	500MWF	300M	2P6	130MN	2MA	VLG	OBS	.	2	
AFY37	PG	TO72	L06	32V	.	OV3	20MA	90C	112MWF	400M	OR4	10MN	2MA	TUG	SID	AF239	2N3783	1
AFY38	PG	TO72	L06	.	10V	.	10MA	75C	110MWF	190M	1P	70/150	1MA	VLA	OBS	AF106	2N3283	2
AFY39	PG	TO1H	L06	32V	.	OV3	30MA	90C	225MWF	300M	1R5	20MN	3MA	VLA	SID	AF239	2N3283	1
AFY40	PG	TO72	L06	32V	20V	OV5	20MA	90C	120MWF	350M	.	10MN	1.5MA	ULA	VAL	AF239S	2N3783	1
AFY40R	PG	TO72	L06	20V	15V	OV5	10MA	75C	120MWF	300M	.	10MN	1.5MA	FVG	VAL	AF239S	2N3783	1
AFY41	PG	TO72	L06	30V	25V	OV3	100MA	100C	60MWF	350M	.	40MN	5MA	FVG	VAL	AF239S	2N3783	1
AFY42	PG	TO72	L06	30V	25V	OV3	10MA	90C	112MWF	350M	OR3	10MN	2MA	TUO	SID	AF239	2N3783	1
AFY60	PG	TO18	L01	12V	9V	.	10MA	75C	75MWF	2M	14P	25/150	1MA	RLA	OBS	OC44N	2N2614	2
AFY61	PG	TO18	L01	10V	9V	.	10MA	75C	75MWF	5M	14P	45/250	1MA	RLA	OBS	OC44N	2N2614	2
AFY66	PG	TO18	L01	12V	10V	.	100MA	75C	125MWF	4M	18P	50/150	10MA	RMS	OBS	ASY27	2N1307	2
AFY71	PG	TO18	L01	10V	10V	.	10MA	75C	55MWF	15M	3P5	20MN	1MA	RLG	OBS	OC44N	2N2614	2
AFY75	PG	TO18	L01	15V	15V	.	10MA	75C	55MWF	17M	3P5	20/150	1MA	RLG	OBS	OC44N	2N2614	2
AFZ10	PG	TO72	L51	20V	10V	OV5	75MA	75C	70MWF	90M	.	20MN	1MA	FVG	OBS	AF200U	.	1
AFZ11	PG	TO72	L51	20V	10V	OV5	10MA	75C	83MWF	135M	2P	20MN	1MA	VLA	MUB	AF201U	.	1
AFZ12	PG	TO72	L51	20V	10V	OV5	10MA	75C	83MWF	135M	2P	20MN	1MA	VLA	MUB	AF201U	.	1
AL100	PG	TO3	L05	130V	60V	2V	10A	100C	30WH	2M	.	40MN	1A	RHG	ATI	AL103	2N2147	0
AL101	PG	TO3	L05	60V	40V	1V	10A	85C	30WH	3M	.	40MN	1A	RHG	ATI	AL103	2N2147	0
AL102	PG	TO3	L05	130V	60V	2V	6A	100C	30WH	2M	.	40MN	1A	RHH	ATI	AU106	2N5325	0
AL103	PG	TO3	L05	100V	40V	1V	6A	100C	30WH	1M	.	40MN	1A	RHG	ATI	AL103	2N2147	0
AL112	PG	X03	L05	35V	20V	2V	4A	100C	10WH	2M	.	40MN	1A	RHG	ATI	AL103	2N2147	0
AL113	PG	X03	L05	60V	40V	2V	4A	100C	10WH	2M	.	40MN	1A	RHG	ATI	AL103	2N2147	0
ALZ10	PG	OBS	OBS	50V	15V	OV7	250MA	75C	500MWC	20M	.	40MN	4MA	RMS	TFK	AFY18	2N2382	1
ASY10	PG	TO1	L02	36V	30V	.	300MA	85C	150MWF	500K	50P	30/50	100MA	AMS	OBS	AC128	2N2706	2
ASY11	PG	TO1	L02	36V	30V	.	300MA	85C	150MWF	500K	50P	40/70	100MA	AMS	OBS	AC128	2N2706	2
ASY12	PG	TO18	L01	32V	32V	10V	600MA	75C	150MWF	1M	.	20MN	250MA	AMS	OBS	AC128	2N2706	1
ASY13	PG	TO18	L01	60V	60V	10V	600MA	75C	150MWC	800K	.	20MN	250MA	AMS	OBS	AC128	2N2706	0
ASY14	PG	TO18	L01	80V	40V	10V	600MA	75C	150MWF	1M	.	20MN	250MA	AMS	OBS	AC128	2N2706	1
ASY23	PG	TO5	L04	80V	80V	20V	300MA	75C	850MWC	500K	.	30MN	50MA	AMS	OBS	ACY17	2N1188	1
ASY24	PG	TO18	L01	50V	12V	OV7	250MA	85C	100MWF	12M	.	40MN	4MA	RMS	TFK	ASY27	2N1305	1
ASY24B	PG	TO18	L01	35V	10V	OV6	250MA	85C	100MWF	12M	.	40MN	4MA	RMS	OBS	ASY27	2N1305	1
ASY25	PG	TO1	L02	45V	30V	12V	300MA	85C	150MWF	500K	50P	60/100	100MA	AMS	OBS	AC128	2N2706	2
ASY26	PG	TO5	L04	30V	15V	20V	200MA	85C	150MWF	4M	16P	30/80	100MA	RMS	SAS	ASY27	2N1305	1
ASY26RT	PG	TO39	L04	30V	15V	20V	200MA	85C	150MWF	4M	16P	30/80	100MA	RMS	OBS	ASY27	2N1305	2
ASY27	PG	TO5	L04	25V	15V	20V	200MA	85C	150MWF	6M	13P	30MN	100MA	RMS	MUB	ASY27	2N1305	0
ASY27RT	PG	TO39	L04	30V	15V	20V	200MA	85C	150MWF	6M	13P	30MN	100MA	RMS	OBS	ASY27	2N1305	2
ASY28	NG	TO5	L04	30V	15V	20V	200MA	85C	150MWF	4M	16P	20MN	100MA	RMS	MUB	ASY29	2N1304	0
ASY28RT	NG	TO39	L04	30V	15V	20V	200MA	85C	150MWF	4M	16P	20MN	100MA	RMS	OBS	ASY29	2N1304	2
ASY29	NG	TO5	L04	25V	15V	20V	200MA	85C	150MWF	10M	16P	30MN	100MA	RMS	MUB	ASY29	2N1304	0
ASY29RT	NG	TO39	L04	30V	15V	20V	200MA	85C	150MWF	10M	16P	30MN	100MA	RMS	OBS	ASY29	2N1304	2
ASY30	PG	X04	L01	50V	25V	1V	250MA	80C	150MWF	20M	5P	40MN	4MA	RLA	TFK	AF124	2N990	0